



3765Z0

Right Angle Light

Peli leads the way yet again with the new 3765Z0 rechargeable right angle torch. Featuring downcast LEDs for illuminating your path, the 3765Z0 LED torch also features 194 lumens (high) and 92 lumens (low), and a flashing mode. Another first is a built in battery life indicator so you will know your battery level before you go in. Compact, rugged, and lightweight, the 3765Z0 LED light contains the latest technology, Peli's legendary build quality and lifetime guarantee of excellence (where applicable by law). Certified to ATEX Zone 0 (Category 1).

- 4 mode battery level indicating button
- Locking wheel securely holds 4 AA batteries
- Secure clip for hands-free use
- Tethered battery door allows for quick battery change




DIMENSIONS

Length 5.36" (13.6 cm)

MATERIALS

| | |
|---------------|------------------------------------|
| Body | Anti-static Impact Modified PC/PBT |
| O-Ring | Buna-N |
| Lens | Anti-static PMMA |
| Shroud | Anti-static Impact Modified PC/PBT |
| Clip | Anti-static Impact Modified PC/PBT |

COLOURS

 High Visibility Yellow

LIGHT SPECS

| | |
|----------------------------|-----|
| Lamp Type | LED |
| Lamp Secondary Type | LED |

POWER

| | |
|--------------------------------|-------------|
| Battery Size | AA |
| Battery Type | NiMH |
| Battery Quantity | 4 |
| Batteries Included | yes |
| Rechargeable | yes |
| Charge Time | 5 hrs |
| Battery Level Indicator | 3 Blue LEDs |
| Volts | 4.8v |

WEIGHT

Weight With Batteries 14.6 oz (414 gr)

Weight Without Batteries

11.0 oz (312 gr)

SWITCH

Switch Type

Push Button

Light Modes

High / Low / Flashing

CERTIFICATIONS

ATEX Zone 0

OTHER

Minimum Pack

1

Package Code

B

| FL1 STANDARD | HIGH | LOW | DOWNCAST |
|---|---------------|--------------|--------------|
|  | 194 LUMENS | 92 LUMENS | 24 LUMENS |
|  | 3h 30mins | 6h 45mins | 20h 0mins |
|  | 256m | 161m | 24m |
|  | 16392cd | 6454cd | 146cd |
|  | IPX4 | | |

ACCESSORIES



3770F
Battery Charger Base



6061F
Direct Wiring Rig for Fast Charger



8056F
12v Plug-in for Fast Charger

Peli

c/ Provença, 388, Planta 7 • Barcelona, Spain 08025 • Phone: +34 934 674 999
info@peli.com • www.peli.com

Document created on 09-27-24